Datasheet and description

Avide Design Oyster Adair 134W(67+67) with RF Remote

Product code: ADO3S-134W-ADA-2.4G

Brand link: avidelighting.com/qr/ADO3S-134W-ADA-2.4G

ID: AB-190518

Company name: Armin Trade Kft.

Company address: Kossuth utca 22 2/4, 4024 Debrecen

QR code:

Date of issue: 2023-03-22

SPECIFICATIONS

EAN code:	5999097929361
Warranty:	3year(s)
Material:	Acryl+Metal
Working temperature:	-20 + 40°C
Packaging:	1/b 5/c
Certifications:	CE

TECHNICAL DETAILS

Wattage:	134W
Voltage:	200-265V
Beam angle:	120°
Dimmability:	Yes
Lumen output:	9 380lm
Color temperature:	5 000K
Lifetime:	25 000h
Type of LED:	SMD2835
CRI:	80
IP standard:	IP20

BOX PICTURE

Datasheet and description

Avide Design Oyster Adair 134W(67+67) with RF Remote

Product code: ADO3S-134W-ADA-2.4G

Brand link: avidelighting.com/qr/ADO3S-134W-ADA-2.4G

ID: AB-190518

Company name: Armin Trade Kft.

Company address: Kossuth utca 22 2/4, 4024 Debrecen

QR code:

Date of issue: 2023-03-22

PRODUCT SIZE

Diameter:	500mm
Height:	500mm

CARDBOARD BOX

EAN:	5999097929361
Packaging:	1/b 5/c
Dimensions:	535mm x 565mm x 85mm
Net weight:	3 060g
Gross weight:	3 680g

CARTON

EAN:	5999097929378
Packaging:	1/b 5/c
Dimensions:	580mm x 450mm x 560mm
Net weight:	15.3kg
Gross weight:	18.4kg

PALLET EXAMPLE

Height:	
Width:	120cm (std Euro pallet)
Mepth:	80cm (std Euro pallet)
Cartons per pallet:	0carton/pallet
Cartons per row:	
Net weight:	3.06kg
Gross weight:	3.68kg

PRODUCT PICTURE

PRODUCT OUTLINE



Datasheet and description

Avide Design Oyster Adair 134W(67+67) with RF Remote

Product code:	ADO3S-134W-ADA-2.4G
Brand link:	avidelighting.com/qr/ADO3S-134W-ADA-2.4G
ID:	AB-190518
Company name:	Armin Trade Kft.
Company address:	Kossuth utca 22 2/4, 4024 Debrecen

QR code:

Date of issue: 2023-03-22

PRODUCT DESCRIPTION

The new Avide design oysters bring unique style to our home.

There are 3 lighting modes available for each model. The first and second modes use a combination of warm white and cold white LEDs to achieve different lighting effects, while the third mode uses a combination of warm white and cold white LEDs to create a natural white color temperature, doubling the power and brightness as well.

Before the very first use, the remote controller has to be paired with the lamp!

Pairing: Within 5 seconds of power ON, push the marked (WIFI signed) button once shortly. If the pairing was successful, the lamp will blink 3 times and the remote controller is ready to use.

Unpairing: Within 5 seconds of power ON, push the marked (WIFI signed) button 3 times shortly. If the unpairing was successful, the lamp will blink several times.

In addition to switching between modes, the product's RF remote controller also allows you to adjust the brightness and color temperature, and to activate the timer function: Press once for 5 minutes, press twice for 30 minutes and press three times for turn off the timer.

The product has a memory function, so the previously used mode and brightness will be active at the next time you turn it on.