Datasheet and description



Avide Design Oyster Adair 134W(67+67) with RF Remote

Product code: ADO3S-134W-ADA-2.4G

Brand link: avidelighting.com/qr/ADO3S-134W-ADA-2.4G

ID: AB-190518

Company name: Bramcke Hungary Kft.

Company address: Kishatár utca 17., 4031 Debrecen



Date of issue: 2024-09-10

Page: 1/3

SPECIFICATIONS

EAN code: 5999097929361

Warranty: 3year(s)

Material: Acryl+Metal

Working temperature: -20 + 40°C

Packaging: 1/b 5/c

Certifications: CE

TECHNICAL DETAILS

IP standard:

Wattage: 134W Voltage: 200-265V 120° Beam angle: Dimmability: Yes Lumen output: 9 380lm Color temperature: 5 000K Lifetime: 25 000h Type of LED: SMD2835 CRI: 80

IP20

BOX PICTURE



Datasheet and description



Avide Design Oyster Adair 134W(67+67) with RF Remote

Product code: ADO3S-134W-ADA-2.4G

Brand link: avidelighting.com/qr/ADO3S-134W-ADA-2.4G

ID: AB-190518

Company name: Bramcke Hungary Kft.

Company address: Kishatár utca 17., 4031 Debrecen



Date of issue: 2024-09-10

Page: 2/3

PRODUCT SIZE

Diameter: 500mm Height: 500mm

CARDBOARD BOX

EAN: 5999097929361

Packaging: 1/b 5/c

Dimensions: 535mm x 565mm x 85mm

Net weight: 2 466g Gross weight: 3 060g

CARTON

EAN: 5999097929378

Packaging: 1/b 5/c


Dimensions: 580mm x 450mm x 560mm

Net weight: 12.33kg
Gross weight: 15.3kg

PRODUCT PICTURE



PRODUCT OUTLINE



PALLET EXAMPLE

Height:

Width: 120cm (std Euro pallet)

Mepth: 80cm (std Euro pallet)

Cartons per pallet: 0carton/pallet

Cartons per row:

Net weight: 2.466kg Gross weight: 3.06kg

Datasheet and description



Avide Design Oyster Adair 134W(67+67) with RF Remote

Product code: ADO3S-134W-ADA-2.4G

Brand link: avidelighting.com/gr/ADO3S-134W-ADA-2.4G

ID: AB-190518

Company name: Bramcke Hungary Kft.

Company address: Kishatár utca 17., 4031 Debrecen



Date of issue: 2024-09-10

Page: 3/3

PRODUCT DESCRIPTION

The new Avide design oysters bring unique style to our home.

There are 3 lighting modes available for each model. The first and second modes use a combination of warm white and cold white LEDs to achieve different lighting effects, while the third mode uses a combination of warm white and cold white LEDs to create a natural white color temperature, doubling the power and brightness as well.

Before the very first use, the remote controller has to be paired with the lamp!

Pairing: Within 5 seconds of power ON, push the marked (WIFI signed) button once shortly. If the pairing was successful, the lamp will blink 3 times and the remote controller is ready to use.

Unpairing: Within 5 seconds of power ON, push the marked (WIFI signed) button 3 times shortly. If the unpairing was successful, the lamp will blink several times.

In addition to switching between modes, the product's RF remote controller also allows you to adjust the brightness and color temperature, and to activate the timer function: Press once for 5 minutes, press twice for 30 minutes and press three times for turn off the timer.

The product has a memory function, so the previously used mode and brightness will be active at the next time you turn it on.