

Avide Design Oyster Brees 125W(62.5+62.5) with RF Remote

Product code:	ADO3S-125W-BRE-2.4G
Brand link:	avidelighting.com/qr/\$CODE\$
ID:	AB-190518
Company name:	Armin Trade Kft.
Company address:	Kossuth utca 22 2/4, 4024 Debrecen



Page: 1/3

SPECIFICATIONS

EAN code:	5999097929286
Warranty:	
Material:	Acryl+Metal
Working temperature:	-20 + 40°C
Packaging:	5/c
Certifications:	CE

TECHNICAL DETAILS

Wattage:	125W
Voltage:	200-265V
Beam angle:	120°
Dimmability:	Yes
Lumen output:	8 750lm
Color temperature:	5 000K
Lifetime:	25 000h
Energy class:	A+
Type of LED:	SMD2835
CRI:	80
IP standard:	IP20

BOX PICTURE



avide >

Avide Design Oyster Brees 125W(62.5+62.5) with RF Remote

Product code:	ADO3S-125W-BRE-2.4G
Brand link:	avidelighting.com/qr/\$CODE\$
ID:	AB-190518
Company name:	Armin Trade Kft.
Company address:	Kossuth utca 22 2/4, 4024 Debrecen



Page: 2/3

PRODUCT SIZE

Diameter: Height:

480mm 73mm

CARDBOARD BOX

EAN:	5999097929286
Packaging:	5/c
Dimensions:	525mm x 530mm x 120mm
Net weight:	4 160g
Gross weight:	4 900g

PRODUCT PICTURE



PRODUCT OUTLINE

CARTON

EAN:	5999097929293
Packaging:	5/c
Dimensions:	630mm x 550mm x 550mm
Net weight:	20.8kg
Gross weight:	24.5kg

PALLET EXAMPLE

Height:	
Width:	120cm (std Euro pallet)
Mepth:	80cm (std Euro pallet)
Cartons per pallet:	0carton/pallet
Cartons per row:	
Net weight:	4.16kg
Gross weight:	4.9kg



Avide Design Oyster Brees 125W(62.5+62.5) with RF Remote

Product code:	ADO3S-125W-BRE-2.4G
Brand link:	avidelighting.com/qr/\$CODE\$
ID:	AB-190518
Company name:	Armin Trade Kft.
Company address:	Kossuth utca 22 2/4, 4024 Debrecen



Page: 3/3

PRODUCT DESCRIPTION

The new Avide design oysters bring unique style to our home.

There are 3 lighting modes available for each model. The first and second modes use a combination of warm white and cold white LEDs to achieve different lighting effects, while the third mode uses a combination of warm white and cold white LEDs to create a natural white color temperature, doubling the power and brightness as well.

Before the very first use, the remote controller has to be paired with the lamp!

Pairing: Within 5 seconds of power ON, push the marked (WIFI signed) button once shortly. If the pairing was successful, the lamp will blink 3 times and the remote controller is ready to use.

Unpairing: Within 5 seconds of power ON, push the marked (WIFI signed) button 3 times shortly. If the unpairing was successful, the lamp will blink several times.

In addition to switching between modes, the product's RF remote controller also allows you to adjust the brightness and color temperature, and to activate the timer function: Press once for 5 minutes, press twice for 30 minutes and press three times for turn off the timer.

The product has a memory function, so the previously used mode and brightness will be active at the next time you turn it on.